



NEMA Premium

**NEMA**

<b>MOTOR MODEL:</b>	GR3-CI-OP-326T-4-BR-D-50
<b>FACTORY TYPE:</b>	-

**NEMA Cast Iron, ODP**

<b>ELECTRICAL DATA</b>		
	60 Hz	50 Hz
Horsepower	50.0	-
Speed, RPM	1770	1460
Voltage	230/460	190/380
# Phase	3	
Full Load Amps	114.5/57.2	-
Power Factor	0.87	-
Nominal Efficiency	94.5	-
3/4 Load Efficiency	-	-
Service Factor	1.15	1.0
KVA Code	E	E
FL Amps. @ 208 V	126.6	-
Locked Rotor Current	-	-
Start Capacitor	-	
Start Capacitor V	-	
Run Capacitor	-	
Run Capacitor V	-	
Number of Leads	12	
Connection	4D/2D	
Coil Resistance	-	
Date Code	-	
Load	Efficiency %	P.F.
50%	94.05	0.7338
75%	94.3	0.8266
100%	94.5	0.87
<b>FULL LOAD TEMPERATURE RISE</b>		
FL Temp Rise °C	74.0	-
<b>3D Image Link</b>		
<a href="#">GR3-CI-OP-326T-4-BR-D-50</a>		

<b>GENERAL DATA</b>				
Frame Size	326T			
Frame Enclosure	ODP			
Mounting	Rigid			
Insulation Class	F			
Duty	Cont. / S1			
NEMA Design	-			
Frame Material	Cast Iron			
Ingress Protection	23			
Tropicalization	true			
Cable Entry	-			
Feet Removable	-			
Double Drilled	-			
Paint Color	Graphite Gray			
Paint RAL	7024			
Weight lb	654.89			
<b>MECHANICAL DATA</b>				
DE Bearing	6312C3			
NDE Bearing	6311C3			
dB No-Load	-			
Rotor Wk <sup>2</sup> , Lb-Ft <sup>2</sup>	-			
Comp Ring (wavey washer)	-			
<b>TORQUE VALUES</b>			Torque lb-ft	% FLT
Locked Rotor Torque	-	-	-	-
Pull-Up Torque	-	-	-	-
Breakdown Torque	-	-	-	-
Full Load Torque	-	-	-	-
<b>SITE CONDITIONS</b>				
Ambient Temp °C	-			
Altitude Above Sea Level m	-			

\*This report valid for above Date Code and newer models, please contact Techtop for more info.

Techtop Industries  
2815 Colonnades Court  
Peachtree Corners, GA 30071  
Tel: 678-436-5540  
E-Mail: info@techttopind.com



NEMA Premium

<b>MOTOR MODEL:</b>	GR3-CI-OP-326T-4-BR-D-50
<b>FACTORY TYPE:</b>	-

**NEMA**

NEMA Cast Iron, ODP

Non Sinusoidal (VFD) Output 50.0HP, 1770 RPM

Torque Speed (T-n) Curve



Performance Load Values, High Voltage, 60Hz

Torque Values	Torque lb-ft	% FLT	Performance Values
Locked Rotor Torque	-	-	Start Configuration
Pull-Up Torque	-	-	Starting Current (A)
Breakdown Torque	-	-	No-Load Current (A)
Full Load	-	-	No-Load Power Factor

% Load	Horsepower	Current, Amps	Input power, Kilowatts	Speed, RPM	Efficiency	PF
0	-	-	-	-	-	-
25	-	-	-	-	-	-
50	-	-	-	-	94.05	0.7338
75	-	-	-	-	94.3	0.8266
100	-	-	-	-	94.5	0.87
125	-	-	-	-	-	-